

Emergency Luminaires

Single Point Emergency Luminaires

All self-contained, non-maintained, single point fittings shall be provided complete with batteries, charger and DALI electronic control gear. The emergency luminaires shall be either 10W quartz halogen or T5 8W fluorescent as scheduled on the drawings.

Integral Type Emergency Luminaires

Where shown on the drawings, normal lighting luminaries shall incorporate a non-maintained emergency lighting lamp, a self-contained power pack and DALI electronic control gear.

Illuminated Exit Signs

All illuminated exit signs shall incorporate a maintained emergency lighting lamp, a self-contained power pack and DALI electronic control gear.

All exit signs shall be of pictograph type with running man and directional arrows. The signs shall be capable of being mounted on ceiling, wall or suspended.